

50hz Perkins Generator Set Specification

Genset Model	Prime Power	Standby Power	Engine Model	Fuel Consumption	Cylinder	Displacement
	KVA/KW	KVA/KW		L/h		
AP10-I	9/7	10/8	403A-11G1	2.6	3L	1.1
AP10-II	9/7	10/8	403D-11G	2.6	3L	1.1
AP14-I	13/10	14/11	403A-15G1	3.6	3L	1.5
AP14-II	13/10	14/11	403D-15G	3.6	3L	1.5
AP17	15/12	17/13	403A-15G2	5	3L	1.5
AP22-I	20/16	22/18	404A-22G1	5.3	4L	2.2
AP22-II	20/16	22/18	404D-22G	5.3	4L	2.2
AP30	28/22	30/24	404D-22TG	7	4L	2.2
AP72	58/52	72/65	1104A-44TG1	14.8	4L	4.4
AP88-I	80/64	88/71	1104A-44TG2	18.7	4L	4.4
AP88-II	80/64	88/71	1104C-44TAG1	18.6	4L	4.4
AP110	100/80	110/88	1104C-44TAG2	22.6	4L	4.4
AP150	135/108	150/120	1106A-70TG1	38	6L	7
AP165	150/120	165/132	1106A-70TAG2	33.4	6L	7
AP200	180/144	200/160	1106A-70TAG3	41.4	6L	7
AP220-I	200/160	220/176	1106A-70TAG4	47	6L	7